


SmartTM-CC series

Solar charge controller

Suitable for Lithium battery
(Constant Current, Buck)
15A 30W



User Manual

Solar charge controller Smart-CC series User Manual

Dear Clients,

Thanks for selecting the **Smart™-CC** series solar controller. Please take the time to read this user manual, this will help you to take advantage of controller' s new features. This manual gives important recommendations for installing, programming, using and so on. Read it carefully in your own interest please.

1. Description of Function

Smart-CC series intelligent solar controller, is programmable and especially for buck mode LED solar street light system. It includes constant current driver function, which can make the cost of the whole system much lower.

It comes with some outstanding features, such as:

- Can output constant current, output current can be set.
- Automatic power balance 365 mode, 365 days can be lit.
- 5 stages time and dimming can be adjusted
- Can read parameters and running status
- Suitable for one or two Lithium batteries in series
- If battery voltage is low, it can be set to dimming
- Dimming start voltage and percentage can be set
- Auto sleeping during transportation
- Low temperature charging protection
- Charging target voltage and eco voltage can be set
- Day/Night threshold can adjust automatically
- Remote Unit to configure, with LCD display
- IP67, Strong and durable aluminum case
- Full automatic electronic protect function

2. Safety instructions and waiver of liability

2.1 Safety

①The solar charge controller may only be used in PV systems in accordance with this user manual and the specifications of other modules manufacturers. No energy source other than a solar generator may be connected to the solar charge controller.

②Batteries store a large amount of energy, never short circuit a battery under all circumstances. We strongly recommend connecting a fuse directly to the battery to protect any short circuit at the battery wiring.

③Batteries can produce flammable gases. Avoid making sparks, using fire or any naked flame. Make sure that the battery room is ventilated.

④Avoid touching or short circuiting wires or terminals. Be aware that the voltages on special terminals or wires can be as much as twice the battery voltage. Use isolated tools, stand on dry ground, and keep your hands dry.

⑤Keep children away from batteries and the charge controller.


2.2 Liability Exclusion

The manufacturer shall not be liable for damages, especially on the battery, caused by use other than as intended or as mentioned in this manual or if the recommendations of the battery manufacturer are neglected. The manufacturer shall not be liable if there has been service or repair carried out by any unauthorized person, unusual use, wrong installation, or bad system design.


3. Dimensions

3.1 Controller

Unit: mm



3.2 Sensor dimension




Sensor lines length: 400

Hole diameter $\Phi 52$

4. Installation

4.1 Connection sequence

The following diagrams provide an overview of the connections and the proper order.



Hot plugging is prohibited!
Please connect the inductive sensor to R series controller first!

1. Follow the chart, connect the load (positive pole and negative pole) with the corresponding brown and blue cables firstly, then seal them with tape.
2. Connect battery positive pole and negative pole to the corresponding red and black cables, the load will be on after 8s;
3. Connect the panel positive pole and negative pole to the corresponding red and black cables, the load will be off after 4s, and the controller begins to charge.
4. Confirm the LED display status: If the red LED is off and the green LED flashes or constantly light, it is normal; else it means fault, please refer to the **11.2 Faults and Alarms** to identify the reason.

- Make sure the length between battery and controller is as short as possible.
- Recommended minimum wire size: 4mm²;

Solar charge controller Smart-CC series User Manual

4.2 Transportation mode(Load off)

Press the "Back" and "Backlight" key at the same time more than 3s, the remote controller will work in factory mode.

Press the "Test" key in the factory mode, the remote controller displays "Transport OK" and will beep a long sound, the controller enters into transport mode.




If the controller enters transport mode, the red LED is flashing(0.2s/5s) and the remote control displays "Open CP".

4.3 Exit the transportation mode

When the load is properly connected, press the test key or connect the solar more than 1s during daytime, the transport mode will terminate and the controller will work normally.

5.Remote control, Default setting

When Smart-CC series controller is connected to the system, you can setting the controller with SU10G infrared remote controller, as shown below! Detailed setting operations, please read SU10G User Manual.



5.1 Read the parameters

Press the "Data" key of the SU10G to read the setting parameters of the controller.

Num	Name	Factory Default
1	Time1	4H
2	Dim1	100%
3	DimNP1	100%
4	Time2	0H
5	Dim2	100%
6	DimNP2	0%
7	Time3	0H
8	Dim3	100%
9	DimNP3	0%
10	Time4	0H
11	Dim4	100%
12	DimNP4	0%
13	Time5	0H
14	Dim5	100%
15	DimNP5	0%
16	D/N Thr	2.0V
17	D/N Dly	0m
18	Load I	0.3A
19	Dim Auto	Yes
20	Dim V	3.2V
21	Dim %	10%

22	Battery	Li
23	Series	1
24	CVT	3.6V
25	CVR	3.4V
26	LVD	2.6V
27	LVR	3.0V
28	0°C Chg	Yes

5.2 Test function

Press the "Test" key of S/SG-Unit, the controller will turn on load for 30s. During daytime, the testing function can help users to verify correct installation or for system trouble shooting. 30s later the load will automatically turn off.

The relationship between "Test" key press times in the 30s and the output power of the controller is shown in the following table:

"Test" press times	Output power
1	Dimming1
2	Dimming2
3	Dimming3
4	Dimming4
5	Dimming5
6	End of test function

5.3 Read the running status

Press the "Status" key of the SU10G to read the running status of the controller.

Num	Name	Name describe	Unit
	Status:	Charge	
1	Batt V	Battery voltage	V
2	Load I	Load current	A
3	Load V	Load voltage	V
4	PV V	PV voltage	V
5	PV I	PV current	A
6	Energy	Total generating capacity	AH
7	OD Times	Over discharge times	Times
8	FC Times	Fully charge times	Times
9	Day1-HV	A day ago highest voltage	V
10	Day1-LV	A day ago lowest voltage	V
11	Day2-HV	Two days ago highest voltage	V
12	Day2-LV	Two days ago lowest voltage	V
13	Day3-HV	Three days ago highest voltage	V
14	Day3-LV	Three days ago lowest voltage	V

6.Starting up the controller

6.1 Self Test

As soon as the controller is connected to battery, it starts self test. Then the display changes to normal operation.

6.2 Battery Type

Smart-CC series controller applies to Lithium rechargeable battery. The charging target and charging recovery voltage can be set according to customer requirements.

Solar charge controller Smart-CC series User Manual

6.3 0°C Charging Protection

"0°C Chg" can be set to "Yes", "Slow" or "No". When the controller detects that the ambient temperature is higher than 0°C, the charging function is normal. When the ambient temperature is low than 0°C, if the "0°C Chg" is set to "Yes", the charging function is normal, else if the "0°C Chg" is set to "slow", the max charging current is 20% of the rated current, else if the "0°C Chg" is set to "No", the controller does not charge the battery.

The user can select the appropriate charging method.


7. Streetlight Function

For controllers with infrared sensing function(R series), if work mode is set to "Five-stage Night Mode" or "TOT mode", "DelayOff" and "Dim NP" work in "Time3" and "Time4".

"DelayOff" setting range: 10~150s.

"Dim NP" setting range: 0~100%.


7.1 Dusk to Dawn (D2D, no induction function)



If "Time1" is set to "D2D", the controller works in dusk to dawn mode.


1. SMR-CC controller is set to D2D mode, the corresponding dimming setting is still valid.
2. If "Time1" is set to D2D mode, "Time4" can not be set to TOT mode.

7.2 Five-stage Night Mode(Time3, Time4 can induction)



You can set the Time 1-5 and Dim 1-5 with S/SG-Unit.

7.3 TOT mode(Time3, TOT can induction)



If "Time4" is set to "TOT", this mode is TOT mode.

* If "Time4" is set to TOT mode, "Time1" can not set to D2D mode.

8. LVD, LVR, Threshold, Dimming

8.1 Low Voltage Disconnect(LVD)

Low voltage disconnect setting range: 2.4~7.2V.

8.2 Low Voltage Reconnect(LVR)

Low voltage reconnect setting range: 2.6~7.4V.



If the controller goes into low voltage disconnect, it will restore only when the battery being recharged to the recovery voltage.


8.3 Day/Night Threshold, Day/Night Delay

The controller recognizes day and night based on the solar array open circuit voltage. This day/night threshold can be modified according to local light conditions and the solar array used.

Day/Night threshold setting range: 1.0~3.0V.

In the evening, when the solar array open circuit voltage reaches the setting day/night threshold, you can adjust the day/night delay time to make the load turn on a little later.

Day/Night delay time setting range: 0~30min.



1. Day/Night threshold voltage of load disconnect is 0.3V higher than the setting data, means the load will disconnect when the solar voltage at 1.3~3.3V.
2. The controller has an automatic day/night threshold adjustment function. If the lowest voltage of solar array is higher than the setting day/night threshold, the load has no output in first night, 24 hours later the controller can automatically adjust the day/night threshold to meet the requirements of lighting at night.

8.4 Dimming

8.4.1 Auto Dimming

The "Dim Auto" item of SU10G is set to "Yes", set "Dim V" and "Dim %" at the same time, press the "Send" key to set up the controller. When the battery voltage is lower than the voltage of "Dim V", it starts to dimming automatically. Battery voltage reduces per 0.1V, load current decreased according to the set of "Dim %", the minimum output current is 10% of the setting current.



1. If the controller is set to "Dim" or "Auto Dim", the minimum output current can be as low as 0.3A.
2. Dimming voltage should not be greater than the voltage of "CVT" (Charging voltage target). When the battery voltage is reduced to close to the LVD voltage, the output current of the controller is reduced to 0.3A.

Solar charge controller Smart-CC series User Manual

9.Safety Features

	Solar terminal	Battery terminal	Load terminal
Reverse polarity	Protected	Protected	Protected
Short circuit	Protected*1	Protected *2	Switches off immediately
Over current	—	—	Switches off with delay
Reverse Current	Protected	—	—
Over voltage	Max.15V *3	Max. 10V	—
Low voltage	—	—	Switches off
Over temp.	If the temperature reaches the set value, the controller cuts off the load.		

*1.When the PV doesn't charge, the controller will not be damaged if short-circuit just happened in the pv array.

Warning :It is forbidden to short-circuit the PV array during charging .Otherwise ,the controller may be damaged.

*2. Battery must be protected by fuse, or battery will be permanently damaged.

*3. The solar panel voltage should not exceed this limit for a long time.


 **Warning: The combination of different error conditions may cause damage to the controller. Always remove the error before you continue connecting the controller.**

10.Recommended connection of LED

Following connect ways is for the LED lights


(Vf: 2.9V~3.4V; I: 300mA, Power: 1W)

n for number of parallel connection



Number of batteries	Load current	Recommendatory connect way
One Lithium battery	0.3~10A	M=1, N=1~30
Two Lithium batteries		M=2, N=1~15

11.LED indications and Faults & Alarms



11.1LED Display Explanation

LED	Status	Function
Green LED	On	not charging
	Slow flash(0.5/2s)	Charging
	Off	Over voltage protection
Yellow LED	On	Battery is normal
	Slow flash(0.5/2s)	Battery voltage is low
	Fast flash(0.1/0.1s)	Low voltage protection
Red LED	Off	Work normal
	On	The output power is 0
	Fast flash(0.1/0.1s)	Short circuit or Over current protection
	Flash(0.5/0.5s)	Over temperature protection
	Super slow flash (0.2s on/5s off)	Open circuit (transport mode) *1

*1.If the controller is in transport mode, the red LED is super slow flash(0.2s on/5s off), the green and yellow led is off.

*2.Detailed fault information can be read by SU10G remote controller.

11.2Faults & Alarms

Fault	Status	Reason	Remedy
Loads are not powered	Low volt. protection	Battery capacity is low	Load will be reconnected when battery is recharged
	Overcurrent short circuit protection	Loads are over current or short circuit	Switch off all loads, remove short circuit, load will be reconnected after 1 minute automatically
	Over temp. protection	Controller temp. is too high	Load reconnects after temp. reduces
High voltage at battery terminal	Over voltage protection	High battery voltage> (" CVT" +0.2V)	Check if other sources overcharge the battery. If not,controller is damaged.
		Battery wires or battery fuse damaged, battery has high resistance.	Check battery wires, fuse and battery.
Battery is empty after a short time	Low voltage protection	Battery has low capacity	Change battery
Battery can't be charged	Green LED is on	PV panel fault or reverse connection	Check panels and connection wires

Solar charge controller Smart-CC series User Manual

12. Technical Data

	Item	Standard product	SMR1006-CCN32Li
		Suffix description	G: 2.4G wireless remote control (default infrared remote control without suffix); R: Infrared sensing; V: Microwave induction;
Battery Parameters	Max Charging Current	15A	
	Charging voltage target	3.0~9.0V(Programmable)	
	Charging voltage recovery	2.9~8.9V(Programmable)	
	Low voltage disconnect	2.4~7.2V(Programmable)	
	Low voltage reconnect	2.6 ~ 7.4V(Programmable)	
	Battery Type	Lithium	
Panel Parameters	0°C Charging protection	Yes, No, Slow(Programmable)	
	Max volt on Bat. Terminal	10V	
	Max volt on PV terminal	7V(Single cell), 15V(Two lithium batteries in series)	
Load Parameters	Dusk/Dawn detect volt.	1.0~3.0V(Programmable)	
	Day/Night delay time	0~30min(Programmable)	
	Output Current	0.3~10A(Programmable)	
	Max. Output Power	30W	
	Min. Current	0.3A (Dimming)	
	Current precision	±2%	
	Dimming	0~100%(Programmable)	
	Auto dimming	Yes, NO(Programmable)	
	Voltage of start dimming	2.8 ~ Charging voltage target (Programmable)	
System Parameters	Dimming percentage	5~40%(Programmable)	
	Induction delay off time	10~150s(Programmable)	
	Dimming when no people	0~100%(Programmable)	
	Communicaion	Infared	
	Self consumption	15mA@3.2V(Transportation mode)	
	Dimensions	45*82*18.6mm	
	Weight	125g	
	Wire size	2.5~4mm²	
	Ambient temperature	-35~+60°C	
	Ambient humidity	0~100%RH	
	Protection degree	IP67	
	Max Altitude	4000m	